



## CONCEPT

### TECHNICAL DATA

Signal/Noise.....	>82dB (Line)
Crosstalk Damping.....	>65dB (Line)
THD.....	<0.05% (Line)
Frequency response.....	20Hz – 20 kHz
AC IN (230V setting).....	AC220-250V~ 50Hz
AC IN (115V setting).....	AC110-120V~ 60Hz
Power consumption.....	max. 18W
Dimensions.....	482.6(427)xH44.5xD152.0mm (parentheses = without rack ears)
Weight.....	2.6 kg

### LOGISTICS DATA

IMM-2320V2 (without Bluetooth module)	
Order Number.....	2005511
Single unit EAN-13.....	5060502920508
IMM-2320V2B (with Bluetooth module)	
Order Number.....	2005521
Single unit EAN-13.....	5060502920515
Single Carton size.....	535x255x90mm
Single Carton gross weight.....	3.1kg
Units per master carton.....	4
Master carton size.....	560x285x390
Master carton gross weight.....	13.4kg

The IMM-2320V2 Media Preamp/Mixer combines a 3-input stereo mixer with 2 microphone inputs and an internal media player. The auto-talkover feature of the microphone section allows automatic attenuation of the music signal by an adjustable amount when speaking into a microphone. This makes the unit a perfect companion for fitness instructors or presenters who have no hand free to lower the program level while speaking. The internal media player sports an IR remote for added comfort; it also features a jingle player, which runs both in a one-shot and a scheduled mode. Two master outputs with fire evacuation facilities like external mute and emergency signal priority functions complete the feature set of this comprehensive unit. The IMM-2320V2 is the ideal core unit for fitness sound systems, hospitality sound systems and mobile sound systems deployed for educational or promotional applications. Also available with additional built-in Bluetooth module as IMM-2320V2B.

## FEATURES

- 2 stereo inputs with signal-present-LED, rear-panel gain and front-panel level control
- Front panel 3.5mm stereo TRS input
- 2x Mic inputs with rear-side 1/4" TRS connectors
- Voice-specific 2-Band EQ plus "on air" switches for mic inputs
- Adjustable auto talk-over for automatic music level reduction when microphone is used
- Internal media player/tuner with file/folder access for USB thumbdrives/SD cards up to 16GB/2000 songs, MP3 file name readout on large LCD display, regular and random play sequence, elapsed/remain time mode, FM tuner mode with RDS station display, jingle player with up to 3 jingles and additional scheduled play mode
- Two stereo main outputs with independent level control
- 2-Band front-side EQ for main output 1
- 10 LED level meter for main output 1
- Rear-side adjustable maximum level control for each output
- Rear-side tone control for main output 2
- Mono switch and 100Hz HP filter on rear side for main output
- Balanced TRS and Phoenix output connectors for both outputs; additional unbalanced RCA connectors
- Emergency input which shuts down master output when emergency signal comes in and plays emergency signal instead
- Output mute contact to externally mute the output
- Headphone section with volume control and front-side 6.3mm stereo jack
- Unbalanced record output
- Internal wide-voltage swing linear power supply for excellent audio dynamics
- Full metal case with brushed aluminum front panel and detachable rack ears
- AC mains voltage selector switch 115/230V
- CE/ROHS compliant
- Available as IMM-2320V2 without Bluetooth module and as QMM-2320V2B with Bluetooth module

