

Q-LED Lighting

FLUX H4IP+ DMX Channel Chart

DMX Mode	DMX Channel	DMX Value	Setting/Percentage
6 Channel Mode	1) Red	0-255	0 – 100% Intensity
	2) Green	0-255	0 – 100% Intensity
	3) Blue	0-255	0 – 100% Intensity
	4) White	0-255	0 – 100% Intensity
	5) Amber	0-255	0 – 100% Intensity
	6) UV	0-255	0 – 100% Intensity

DMX Mode	DMX Channel	DMX Value	Setting/Percentage
8 Channel Mode	1) Master Dimmer	0-255	0 – 100% Intensity
	2) Strobe	0-10	No Function
		11-255	Strobe Rate (Slow – Fast)
	3) Red	0-255	0 – 100% Intensity
	4) Green	0-255	0 – 100% Intensity
	5) Blue	0-255	0 – 100% Intensity
	6) White	0-255	0 – 100% Intensity
	7) Amber	0-255	0 – 100% Intensity
	8) UV	0-255	0 – 100% Intensity

DMX Mode	DMX Channel	DMX Value	Setting/Percentage
11 Channel Mode	1) Master Dimmer	0-255	0 – 100% Intensity
	2) Strobe	0-10	No Function
		11-255	Strobe Rate (Slow – Fast)
	3) Red	0-255	0 – 100% Intensity
	4) Green	0-255	0 – 100% Intensity
	5) Blue	0-255	0 – 100% Intensity
	6) White	0-255	0 – 100% Intensity
	7) Amber	0-255	0 – 100% Intensity
	8) UV	0-255	0 – 100% Intensity
	9) Colour Macros & Whites	0 – 10	No Function
		11 - 30	R: 100% G: 0-100% B: 0%
		31 - 50	R: 100 – 0% G: 100% B: 0%
		51 - 70	R: 0% G: 100% B: 0-100%
		71 – 90	R: 0% G: 0% B: 100%
		91 - 110	R: 0-100% G: 0% B: 100%
		111-130	R: 100% G: 0% B: 100–0%
		131 - 150	R: 100% G: 0-100% B: 0-100%
		151 – 170	R: 100% G: 100-0% B: 100%
		171 - 200	R: 100% G: 100% B: 100%
		201 - 205	White 1
		206 - 210	White 2
		211 – 215	White 3
		216 – 220	White 4
		221 – 225	White 5
		226 – 230	White 6
		231 – 235	White 7
		236 - 240	White 8
		241 – 245	White 9
		246 – 250	White 10
		251 - 255	White 11
	10) Auto Mode	0 -10	No Function
		11-40	RGB Colour Mixing
		41-70	CMY Colour Mixing
		71-100	RGBA Colour Mixing
		101-130	RGBACMY Colour Mixing
		131-160	RGB Colour Changing
		161-190	CMY Colour Changing
		191- 220	RGBA Colour Changing
		221-255	RGBACMY Colour Changing
	11) Speed	0 – 255	Slow – Fast

